

# **Z-Wave Touchpad Lever**

**KA214** 



#### **Z-Wave Plus Enabled**

Upgrade to a Z-Wave smart lock for compatibility with most smart home systems.



### **Away Mode**

This is a safety feature when you leave for vacation or a long trip, disabling all User PIN Codes.



#### **PIN Code**

Supports 250 PIN Codes ranging 4-10 digits.



#### Silent Mode

The sounds when pressing the keypad can be muted. However you will still hear low battery warnings and system alerts.



### **One-Time PIN Code**

Share One-Time PIN Codes with friends, family members, or service providers.



### **Wrong Entry Limit**

After 10 failed unlocking attempts, the device will switch off for 3 minutes.



#### **One-Touch Locking**

Press any of the buttons on the keypad for 2 seconds to lock the device without a key.



## **Backup Keyway**

Comes with 2 keys for constant access to your home.



### **Auto Lock**

Set your lock to automatically lock after a certain period of time.



#### **Easy Installation**

Installs in minutes with just a screwdriver, easy to DIY.







Oil Rubbed Bronze



Matte Black



# **Specifications**

Bolt Type	Latch	IoT Connection	Z-Wave
Application	Residential Door	Keyway	SC1
Main Material	Zinc Alloy	Wrong-Entry Alarm	10 times/3min
Battery	4 AA Alkaline Batteries	Low Battery Alarm	Yes
Keypad Type	Backlit Touchpad	IP Rating	IP65 Rated Dust Proof Water Proof
PIN Code	Master PIN Code x 1 User PIN Code x 250 One-Time PIN Code x 1	Working Temperature	-22 to 140°F (-30-60°C)
Code Length	4-10	Door Prep Size	2.13 inch (54mm)
Fingerprint Quantity	N/A	Door Thickness	1.38 to 1.97 inch (35-50mm)
Safety Function	Auto Lock One-Time PIN Code Lockout Mode Away Mode	Backset	2.36/2.76 inch (60mm/70mm) Adjustable

# What's in the box

